

Your music where you want it— wirelessly. HP Wireless Audio transforms any PC⁽¹⁾ into a fully integrated wireless audio system. The same state-of-the-art sound delivered to 4 different locations in your home.

Premium audio performance.

Supports 5.1 speaker systems. Zero lag time. No interference. Advanced tri-band-2.4, 5.2, 5.8GHz- wireless connection.

Powerful 4-zone range

Turn your $\mathsf{PC}^{(1)}$ into a full-fledged home audio system. The same amazing audio streams to 4 different areas in your home.

Easy & direct set-up.

HP Wireless Audio connects in few simple steps. This state-of-the-art software is so intuitive, it automatically 'sees' your speakers and links them together. Pair it and forget it. Never connect them again.

Far-reaching 100ft (30m) span.

HP Wireless Audio streams your sound- music, movies or games- up to an incredible 100ft (30m) in any direction.

Features and Benefits

- Small transmitter plugs into your PC USB port.
- Compact receiver tucks away anywhere. Its small size equals a bar of soap
- Intuitive software takes the guess work out of managing your system.
- Superb, uncompressed audio quality with 5.1 audio support. • Easy. Intuitive. Exclusive.⁽²⁾ State-of-the-art software automatically 'sees'
- & links your speakers in a few simple steps. · Pair it and forget it. Speakers & headphones automatically connect each time.
- Streams same audio to 4 different zones.
- Transmitter blasts audio up to an impressive 100ft (30m) in any direction.(3
- No interference with other devices. Tri-band frequency- 2.4, 5.2,
- 5.8GHZ— delivers the best possible wireless performance.
- No lag time. Zero latency. Your movies and games are always in sync.

Compatibility

· Any notebook or desktop PC with an available USB port

Technical Specifications

- Up to 5.1 speaker systems
- Tri-band connectivity (2.4, 5.2, 5.8Ghz)
- Low latency
- 100ft (30m) bi-directional range
- 4 audio connectors: R/L analog RCA jacks, 3.5mm, mini TOSLINK, Coax RCA-style S/PDIF

System Requirements

• Any notebook or desktop PC⁽¹⁾ with an available USB port

What's in the Box

- Transmitter
- Receiver
- Power Adapter
- User Guide Software CD
- Warranty

Warranty and Support

- · One-year, worldwide parts-and-labor limited warranty
- 24x7 HP technical phone support during warranty period

Additional Information

Questions about the HP Wireless Audio? Look us up online at www.hp.com

- HP Part Number: QF299AA#ABC
- UPC Code: 886111912025
- ITF 14 Master Carton: 10886111912022
- Tariff: 8518302000
- Country of Origin: China
- Master Carton Quantity: 10
- Master Carton Dimensions:
- 16.34" (L) x 15.16" (W) x 7.48" (H) Master Carton Weight: 16.20 lbs
- Packaged Product Dimensions:
- 8.58" (L) x 5.98" (W) x 2.48" (H/D)
- **Unpackaged Product Dimensions:** Transmitter: 3.47" (L) x 1.22" (W) x 0.59" (H) Receiver: 3.15" (L) x 3.07" (W) x 1.26" (H)
- Packaged Product Weight: 1.43 lbs
- Unpackaged Product Weight: 0.39 lbs
- Pallet Information: -Cartons per layer: 6
- -Layers: 10
- -Cartons per pallet: 60
- -Products per layer: 60 -Total products per pallet: 600



2x the connectors. HP Wireless Audio is the first system on that market that features 4 connectors: 2 analog, 2 digital.^[2]R/L analog RCA jacks, 3.5mm mini, TOSLINK line-out, Coax RCA-style S/PDIF



KleerNet or powered speakers compatible. Works great with Monster, Astro Gaming, Boston Acoustics or your own powered speakers.⁽⁴⁾

Everybody On



VISIT WWW.HP.COM FOR MORE DETAILS!

©2011 Hewlett-Packard Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing shall be construed as constituting an additional warranty HP shall not be liable for technical or editorial errors or omissions contained herein. Actual product may vary from image shown on datasheet.

⁽²⁾ Requires Microsoft[®] Windows[®] XP, Win7, Vista[™] operating systems.
⁽²⁾ Compared to but not limited to the following brands as of 9/1/2011: Creative Wireless Sound Blaster, Beatbox, Bluetooth Audio Dongle & Receiver, Intel WiDJ, Sony ALTUS S-AIR Wireless Audio Receiver and Transmitter, Apple Airport Extreme Base Station + Airport Express Base Station.

⁽³⁾Range reaches up to 100ft (30m) in-home and depends on structure and layout of walls.

⁽⁴⁾ Each set of powered speakers require an individual receiver box to be functional

